

SOP02573

Updating Xantrex Inverter Firmware (With Fault)

Prepare a USB Flash Drive per SOP02573 steps 1 through 8.

1



Disconnect the unit from shore power

2



Ensure the inverter is turned on by depressing the button and making sure it is ON on the Dometic Touchscreen.

3



Plug the flash drive into the inverter

4



The LED will blink green/orange for about 15 seconds

5



Once the LED has finished flashing. It will be green for about 5 seconds and then shut off. Remove the flash drive at this point.

6



Turn off the battery disconnect and unpress the button on the inverter for ONE minute.

7



Turn on the battery disconnect and the inverter. If the Dometic system shuts it off, turn it on through the touch screens.

8



Verify the update took place by using a mirror to view the inverter display. And press the middle button on the display until you see a "U3 01 05" displayed.

9

Technical Data:

Notes: